

OSB5XME3C1E VER C.0


#### **■**Features


- · Highest Luminous Flux
- · Super Energy Efficiency
- Long Lifetime Operation
- Superior ESD protection
- Superior UV Resistance

## **■**Applications

- Read lights (car, bus, aircraft)
- Portable (flashlight, bicycle)
- Bollards / Security / Garden
- Traffic signaling / Beacons
- In door / Out door Commercial lights
- · Automotive Ext

### **Outline Dimension**






5.5.5

(Ta=25°C)

(Ta=25°C)




ESD Protection Diode Unit:mm Tolerance:±0.30mm

# **■**Absolute Maximum Rating

Item	Symbol	Value	Unit
DC Forward Current	$I_{\mathrm{F}}$	800	mA
Pulse Forward Current*	$I_{FP}$	1000	mA
Reverse Voltage	$V_R$	5	V
Power Dissipation	$P_{\mathrm{D}}$	3200	mW
Operating Temperature	Topr	-30 ~ +85	$^{\circ}\!\mathbb{C}$
Storage Temperature	Tstg	-40~ +100	$^{\circ}\!\mathbb{C}$
Lead Soldering Temperature	Tsol	260°€ /5sec	-

### Directivity





### **■**Electrical -Optical Characteristics

Item	Symbol	Condition	Min.	Тур.	Max.	Unit
DC Forward Voltage	$V_{\mathrm{F}}$	I <sub>F</sub> =350mA	3.0	3.3	4.0	V
		I <sub>F</sub> =700mA	3.5	3.8	4.5	V
DC Reverse Current	$I_R$	$V_R=5V$	-	-	10	μΑ
Domi. Wavelength	$\lambda_{\mathrm{D}}$	I <sub>F</sub> =700mA	465	470	475	nm
Luminous Flux	Фи	I <sub>F</sub> =700mA	20	30	-	lm
50% Power Angle	2θ1/2	I <sub>F</sub> =700mA	-	120	-	deg

Note: Don't drive at rated current more than 5s without heat sink for Xeon 3 emitter series.

### **■Forward Operating Current (DC)**















<sup>\*</sup>Pulse width Max.10ms Duty ratio max 1/10



Yeon	3	<b>Power</b>	Rlue	LED
	_ 7			4 4 4

OSB5XME3C1E VER C.0

# **■** Handling of Silicone Lens LEDs

Notes for handling of silicone lens LEDs

- Please do not use a force of over 3kgf impact or pressure on the silicone lens, otherwise it will cause a catastrophic failure.
- The LEDs should only be picked up by making contact with the sides of the LED body.
- Avoid touching the silicone lens especially by sharp tools such as Tweezers.
- Avoid leaving fingerprints on the silicone lens.
- Please store the LEDs away from dusty areas or seal the product against dust.
- When populating boards in SMT production, there are basically no restrictions regarding the form of the pick and place nozzle, except that mechanical pressure on the silicone lens must be prevented.
- Please do not mold over the silicone lens with another resin. (epoxy, urethane, etc)



